



CBH

EXH

**FEATURES-SPECIFICATIONS**

**Applications**

CBH Series circuit breaker handles are for use with the following Series of Killark enclosures: XB, XJB, DB.

- These devices may be used to activate circuit breakers, motor circuit protectors, and nonfusible disconnects
- Complete handle mechanisms include external handle and lockout, internal switching mechanism, and adjustable shaft
- Consult factory for installation data, and hazardous location suitability

CBH CIRCUIT BREAKER HANDLES							
CATALOG NUMBER						CIRCUIT BREAKER FRAME TYPE	
COMPLETE ASSEMBLY <sup>①</sup>	MOUNTING PAN <sup>②</sup>	SHAFT				CUTLER HAMMER	SQUARE D
		FOR 6" DEEP BOX	FOR 8" DEEP BOX	FOR 12" DEEP BOX	FOR 20" DEEP BOX		
CBH-114	CBH-1P	CBH-6S	CBH-8S	CBH-12S	CBH-20S	EHD, FDB, FD, HFD, FDC, HMCP-150	—
CBH-118	CBH-1P	CBH-6S	CBH-8S	CBH-12S	CBH-20S	—	FAL, FHL
CBH-120	CBH-1P	CBH-6S	CBH-8S	CBH-12S	CBH-20S	30, 60 Amp N.F. Switch	—
CBH-213	CBH-3P	CBH-6S	CBH-8S	CBH-12S	CBH-20S	DK, KDB, KD,HKD, KDC, HMCP-400	—
CBH-216	CBH-3P	CBH-6S	CBH-8S	CBH-12S	CBH-20S	JDB, JD, HJD, JDC, HMCP-250	—

<sup>①</sup>CBH-114 thru CBH-120 provided with CBH-6S shaft. CBH-213 thru CBH-216 provided with CBH-8S shaft.  
<sup>②</sup>Breaker mounting pan is not included in complete assembly.

**Circuit Breaker Handles**

For use with enclosure type B7E-DB-EXB-XB-XJB

- Used to activate circuit breakers and motor circuit protectors from front cover
- Factory or field installed in a 3/4" NPSM opening for EXH1 & EXH2 and a 1-1/4" NPSM for EXH3
- Has provision for Lock-On and Lock-Off with up to three padlocks
- Consists of an external handle mechanism with through-the-enclosure shaft and internal toggle mechanism and breaker pan

Submit sketch showing the desired location of internal breaker for factory location of handle mechanism.

Order as separate option with enclosure for factory installation or by Catalog Number for field installation.

Consult factory for handle mechanism for fused and non-fused disconnect switches.

EXH CIRCUIT BREAKER HANDLE WITH SHAFT AND PAN					
CATALOG NUMBER			BREAKER MANUFACTURER	BREAKER FRAMES TO OPERATE	MAX. AMPS
6" DEEP BOX	8" DEEP BOX	10" DEEP BOX			
EXH1A6	EXH1A8	EXH1A10	GE	TEB-TED-THED-TEL	150
			ITE/Siemens	ED2-ED4-ED6-HED4-HED6	125
			Square D	FAL-FHL-FCL	100
			Cutler Hammer	EHD-FDB-FD-HFD-FDC-HMCP	150
N/A	EXH1B8	EXH1B10	GE	TFJ-TFK-THFK-TFL	225
			Square D	KAL-KHL-KCL	250
N/A	EXH2C8	EXH2C10	Cutler Hammer	JDB-JD-HJD-JDC	250
			Cutler Hammer	DK-KDB-KD-HKD-KDC	400
N/A	EXH3D8	EXH3D10	GE	TJJ-TJK4-TJK6-THJK4-THJK6	600
			ITE/Siemens	FXD6-FD6-HFD6-CFD6	250
			ITE/Siemens	JXD2-JXD6-JD6-HJD6-HHJD6-CJD6	400
			ITE/Siemens	LXD6-LD6-HKD6-HHLD6-CLD6	600
			Square D	LAL-LHL	400
			Cutler Hammer	LDB-LD-HLD-LDC	600
N/A	N/A	EXH3E10	GE	TKM8-THKM8-TKM12-THKM12	1200
			ITE/Siemens	MXD6-MD6-HMXD6-HMD6-CMD6	800
			ITE/Siemens	NXD6-ND6-HNXD6-HND6-CND6	1200
			Square D	LCL	600
			Square D	MAL-MHL	1000
			Cutler Hammer	ND-HND-NDC	1200

